

B.02 Canonical forms of the state model

There are several canonical forms for the state equations, all of which can be found via basis transformations from other forms.

Phase-variable canonical form

The **phase-variable canonical form** is represented by the SISO¹ state model

$$\dot{\mathbf{x}}_c = A_c \mathbf{x}_c + B_c u \tag{1a}$$

$$y = C_c \mathbf{x}_c + D_c u \tag{1b}$$

phase-variable canonical form

1. There are phase-variable canonical forms for MIMO systems as well, but these are less standardized.

where

$$A_c = \begin{bmatrix} 0 & 1 & 0 & \dots & 0 & 0 \\ 0 & 0 & 1 & & 0 & 0 \\ \vdots & \vdots & & \ddots & & \vdots \\ 0 & 0 & 0 & & 1 & 0 \\ 0 & 0 & 0 & \dots & 0 & 1 \\ -a_0 & -a_1 & -a_2 & \dots & -a_{n-2} & -a_{n-1} \end{bmatrix}, \quad B_c = \begin{bmatrix} 0 \\ 0 \\ \vdots \\ 0 \\ 0 \\ 1 \end{bmatrix}, \tag{1c}$$

$$C_c = [c_1 \quad c_2 \quad \dots \quad c_n], \text{ and } D_c = [d_1]. \tag{1d}$$

In order to transform a SISO system (A, B, C, D) with state vector \mathbf{x} to phase-variable canonical form, we change bases via the substitution of $\mathbf{x} = T_c \mathbf{x}_c$ into the original system, which gives

$$A_c = T_c^{-1} A T_c, \quad B_c = T_c^{-1} B, \tag{2a}$$

$$C_c = C T_c, \text{ and } D_c = D. \tag{2b}$$

The special form of Equation 1 yields the following characteristic polynomial:

$$s^n + a_{n-1} s^{n-1} + \dots + a_1 s + a_0. \tag{3}$$

Recall that eigenvalues of a system are invariant to basis change, and therefore so is

its characteristic polynomial. From this we can conclude that A_c can be completely determined by finding the characteristic polynomial of the original matrix A . B_c is already fully determined, but C_c and D_c remain undetermined. They may be found by discovering the transformation matrix T_c and substituting it into Equation 2.

Finding the phase-variable canonical transformation

The phase-variable canonical transformation matrix T_c can be found by relating the controllability matrices of the original form and the canonical form.

Theorem B.4: phase-variable canonical transformation

The transformation matrix from a system representation with controllability matrix U to a phase-variable canonical transformation with controllability matrix U_c is

$$T_c = U_c U^{-1} \tag{4}$$

By the Definition of the controllability matrix, the original controllability matrix is

$$U = [B \mid AB \mid A^2B \mid \dots \mid A^{n-1}B] \tag{5}$$

and that of the canonical form is

$$U_c = [B_c \mid A_c B_c \mid A_c^2 B_c \mid \dots \mid A_c^{n-1} B_c] \tag{6}$$

Note that U and U_c are both known from above. We relate the two forms by applying Equation 2 to Equation 6 to yield

$$U_c = [T_c^{-1} B \mid T_c^{-1} A B \mid T_c^{-1} A^2 B \mid \dots \mid T_c^{-1} A^{n-1} B] \tag{7a}$$

$$= T_c U, \tag{7b}$$

to yield

$$T_c = U_c U^{-1}.$$

C

Physical topics